R. C. Tronics Incorporated


2573 East Kercher Road Goshen, Indiana 46528 Toll Free 1-866-457-7790

## **DAT-01367-00XXX**

Phone 1-574-642-3857
Fax 1-574-642-3858
http://www.rctronics.com

## **06 Conductor Data Cable**

Viewed with Tyco Connector Plug-In Face Down.



## DAT-01367-00XXX

Carol C-4066A, 22 AWG, Stranded 7/30/8, unshielded six conductor cable.

Cut each jacket end 4 inches long, remove jacket on each end.

Place connector into insertion equipment, start with #8 and complete with #1

Requires one (2) Tyco/Amp. 643813-6 connector & Tyco/Amp. 643075-6 end cap.

Terminate right end as shown.

CHECK CABLE WITH CABLE CHECKER

#1 BLACK, #2 RED, #3 GREEN, #4 BROWN,

#5 BLUE, #6, ORANGE, #7 YELLOW, #8 WHITE

D A T	1st three Letters = Data Cable
0 0 0 0	2nd five numbers = Print Number
0	3rd two numbers = Configuration
0	4th two numbers = Length In Feet
0	5th last digit = Length In Inches